

SKM 945 @

RF Wireless Systems | evolution wireless @

Mod. No. 21637

General Description

A truly professional stage microphone, the super-cardioid SKM 945 @ handheld transmitter easily cuts through the mix, offering clarity and projection even with high ambient sound levels. It can be combined with any of the receivers from the ew 500 @ Series or the EM 550 @. The SKM 945 @ features nine frequency banks with up to 20 directly accessible presets each – ready for immediate use.



Technical Data

RF frequency range	518–866 MHz
Transmission frequencies	1,440
Presets	max. 20
Switching bandwidth	36 MHz
Peak deviation	± 48 kHz
Compander	HDX
AF frequency response	40–18,000 Hz
Signal-to-noise ratio	> 115 dB(A)
THD	< 0.9 %
In compliance with ETS 300422	2, ETS 300445, CE , FCC
Power supply	2 x 1.5 V (AA)
RF output power	30 mW
Operating time	> 8 hrs
Dimensions	d = 50 mm (1.97"),
	I = 225 mm (8.86")
Weight	450 g (15.87 oz)
Transducer	dynamic
Sensitivity	1,6 mV/Pa
Max. SPL	154 dB
Pick-up pattern	super-cardioid

- 1440 tunable UHF frequencies for interference-free reception
- Absolutely reliable transmission and extended range due to high RF output power
- Pilot tone squelch for eliminating RF interference when transmitter is turned off Pilo
- Rugged metal housing
- Backlit display (lights up when a button is pushed)
- User-friendly menu operation
- Lock function avoids accidental changing of settings
- HDX compander for crystal-clear sound
- 4-step battery status display, also transmitted to receiver
- Mute function
- Wide range of accessories adapts the handheld transmitter to any requirement
- Delivery includes: 1 SKM 945 @ handheld transmitter (dynamic, super-cardioid)
 - 1 MZQ 1 microphone clip, 1 protective pouch
 - 2 batteries AA size

Cat. No. 500256
Cat. No. 500257
Cat. No. 500258
Cat. No. 500259
Cat. No. 500260

Recommended Accessories	
CC 2 system case	Cat. No. 009826
■ MZW 1 foam windshield, anthracite	Cat. No. 004839
■ BA 2015 accu pack	Cat. No. 009950
L 2015 charging unit	Cat. No. 009828
■ KEN 1	Cat. No. 083322